

IR-RX2

Portable Infrared Receiver



CONTACTA INFRARED (IR)

The Contacta Portable Infrared Receiver is a four-channel Receiver, compatible with our infrared transmitters using frequencies 2.3MHz and 2.8MHz. It features automatic gain control and high sensitivity for incoming infrared signals.

The Portable Infrared Receiver uses rechargeable batteries and can be recharged with the 5 Bay IR Receiver Charger (IR-RX2-DC5). It can be paired with headphones (HP1) or the Inductive Neck Loop (NL1).

Physical Data

Dimensions	Height – 4.40" Width – 2.75" Depth – 0.86"
Weight	0.44lbs
Finish	Black

Technical Data

Frequencies	2.3MHz / 2.8MHz
Battery	2x AAA rechargeable, type NiMH, 1.2V 750mAh
Battery Life	Approximately 20 hours
Frequency Response	60Hz to 12kHz +-3dB
SNR	54dB not weighted
Max Output	6mW
Settings	Volume Adjustment 4 channel selection - rotary control



Applications

- › Conference and Meeting Rooms
- › Court Buildings
- › Lecture Halls, Schools, and Universities
- › Cinemas and Theatres
- › Places of Worship
- › Museums

Includes

- › Belt clip
- › Lanyard
- › 2x Rechargeable Batteries

contacta

Phone: (616) 392-3400
Email: sales@contactainc.com
www.contactainc.com